

## PRODUCT DATASHEET

### SMART+ WIFI Nightlight Plug EU White

SMART+ WIFI Nightlight Plug EU | Nightlight integrated plug with smart socket to control non smart devices with WiFi technology



---

#### Areas of application

- Wherever non-smart devices need to be integrated into compatible smart home systems
- Nightlight as an orientation light or safety light for children's rooms, stairs, or bedrooms

---

#### Product benefits

- Integrates conventional electric equipment into compatible smart home systems
- Nightlight as an orientation light or safety light at night or in dark area
- Nightlight separately controllable and dimmable
- Simple connection of electric devices via standard socket
- Monitors energy usage of connected devices and tracks the energy consumption
- Enables switching of conventional light sources and other electric devices

---

#### Product features


- Controllable via voice control available: Google Assistant or Amazon Alexa
- Nightlight integrated with warm white and dimmable
- High switching power: up to 3,680 W / 16 A
- Energy meter
- Scheduling
- Network protocol: WiFi (2.4 GHz)
- Controllable via SMART+ App (with minimum Android 8.0 or iOS 14.0)

## TECHNICAL DATA

### Electrical data

Nominal voltage	230 V
Nominal current	16 A
Mains frequency	50 Hz

### Dimensions & Weight



Product weight	118.00 g
Length	57 mm
Width	84 mm
Height	57 mm

### Lifespan

Number of switching cycles	10000
----------------------------	-------

### Colors & materials

Product color	White
---------------	-------

### Temperatures & operating conditions

Ambient temperature range	-20...+35 °C
---------------------------	--------------

### Capabilities

Type of connection	Plug
Compatible smart home technology	Amazon Alexa / Google Home

### Certificates & Standards







Standards	CE
Protection class	I
Type of protection	IP20

### Safety advice

- Disconnect devices which generate heat from the mains, after use in order to avoid them being accidentally switched on.
- Very high capacitive and inductive loads may in some cases lead to destruction of the device or reduction in the number of switching cycles.
- Do not use the SMART+ Plug in conjunction with medical equipment.

- To be connected to an automatic circuit breaker (for max. 16 A)
- Product in protection class I. All electrically conductive, metallic housing parts that can absorb voltage during operation or during maintenance in the event of a fault must be continuously connected to the protective earthing conductor.

## DOWNLOAD DATA

Documents and certificates		Document name
	User instruction / safety instructions	SMART+ WIFI NIGHTLIGHT PLUG EU
	Addon technical information	Wifi remote control compatibility list
	Addon technical information	Wifi remote control compatibility list (DE)
	Legal information	Safety insert G11225554
	Declarations of conformity	SMART WIFI NIGHTLIGHT PLUG EU    LEDV
	EU Data Act	SMART WiFi Plugs

## LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4099854418211	Folding box 1	62 mm x 96 mm x 109 mm	165.00 g	0.65 dm <sup>3</sup>
4099854418228	Shipping box 4	200 mm x 130 mm x 121 mm	733.00 g	3.15 dm <sup>3</sup>

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

## References / Links

- Further information and frequently asked questions (FAQs) at [www.ledvance.com/en-int/home-lighting/services/faq](http://www.ledvance.com/en-int/home-lighting/services/faq)

## DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.