

PRODUCT DATASHEET

SMART+ MATTER Orbis Downlight Round 200mm Tunable White

SMART+ MATTER Surface Downlight | Smart recess surface downlight with integrated driver TW and dimmable



Areas of application

- Indoor applications
- Corridors, entrance areas, stairwells, living rooms, basements
- Bedrooms
- Kitchens

Product benefits

- Creating individual light scenes according to your needs with cold white to warm white (3000 K to 6500 K)
- Surface downlight

Product features

- Controllable via SMART+ App (with minimum Android 8.0 or iOS 14.0) or any other Matter-compatible platforms
- Controllable via voice control available: Google Assistant or Amazon Alexa
- Adjustable color temperature via Tunable White: 3,000...6,500 K
- Dimmable
- Network protocol: Matter over WiFi (2.4 GHz)
- Housing material: metal

TECHNICAL DATA

Electrical data

Nominal wattage	12.00 W
Nominal voltage	220...240 V
Mains frequency	50...60 Hz
Nominal current	60.000 mA
Power factor λ	> 0.70
Total harmonic distortion	< 20 %
Protection class	I
Operating mode	External LED driver

Photometrical data

Luminous flux	900 lm
Total luminous flux of contained light sources	1250 lm
Luminous efficacy	83 lm/W
Color temperature	3000...6500 K
Light color (designation)	Tunable White
Color rendering index Ra	≥80
Standard deviation of color matching	< 6 sdc _m
Photobiological safety group acc. to EN62778	RG0
Beam angle	110 °

Dimensions & Weight

Diameter	200.00 mm
Height	40.00 mm
Product weight	430.00 g

SMART WIFI ORBIS DOWNLIGHT

Materials & Colors

Product color	White
Housing color	White
Body material	Aluminum
Cover material	Polystyrene (PS)
Glow Wire Test according to IEC 60695-2-12	650 °C

Application & Mounting

Ambient temperature range	-20...40 °C
Temperature range at storage	-20...+70 °C
Type of connection	Screw terminal
Type of protection	IP20
Protection class IK (shock resistance)	IK03
Dimmable	Yes
Type of dimming	WiFi
Mounting type	Surface
Mounting location	Ceiling
Application environment	Indoor
With light source	Yes

Lifespan

Lifespan L70/B50 at 25 °C	25000 h
Number of switching cycles	15000

Emergency lighting

Type of emergency operation test	None
----------------------------------	------

Certificates & Standards

Standards	CE / UKCA
Ball shot safe	No
Replaceable light source (EPREL)	Not replaceable

Additional product data

Product remark	Available from October 2025 / Reset settings to default by switching the product on for five seconds and off for five seconds and repeating this five times.
----------------	--

EQUIPMENT / ACCESSORIES

- For control via SMART+ App, a smartphone or tablet is required (with minimum Android 8.0 or iOS 14.0)
- Complete mounting and connecting accessories included

Safety advice

- All electrical connections must be made by a qualified person.
- Caution, risk of electric shock.
- Product in protection class I. All electrically conductive, metallic housing parts that can absorb voltage during operation or during maintenance in the event of a fault must be continuously connected to the protective earthing conductor.

DOWNLOAD DATA

Documents and certificates		Document name
	User instruction / safety instructions	SMART + WIFI ORBIS DOWNLIGH ROUND
	Addon technical information	Wifi remote control compatibility list
	Addon technical information	Wifi remote control compatibility list (DE)
	Declarations of conformity	CE declaration SMART Matter Downlight
	Declarations of conformity UKCA	UKCA Declaration Orbis Spiral
	Declarations of conformity UKCA	UKCA declaration SMART Matter Downlight
	EU Data Act	SMART MATTER Lamps Luminaires Plugs

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4099854475597	Folding box 1	230 mm x 48 mm x 232 mm	634.00 g	2.56 dm ³
4099854475603	Shipping box 10	478 mm x 263 mm x 255 mm	6340.00 g	32.06 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

References / Links

– Further information and frequently asked questions (FAQs) at www.ledvance.com/en-int/home-lighting/services/faq

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.