

PRODUCT DATASHEET SMART+ WIFI PLUG UK

SMART+ Plug | Plug with smart socket to control non-smart devices with WiFi technology, pairable with Remote Controller



Areas of application

 Wherever non-smart devices need to be integrated into compatible smart home systems

Product benefits

- Integrates conventional electric equipment into compatible smart home systems
- Enables switching of conventional light sources and other electric devices
- Simple connection of electric devices via standard socket
- Monitors energy usage of connected devices and tracks the energy consumption

Product features

- Controllable via LEDVANCE SMART+ App (with minimum Android 8.0 or iOS 14.0)
- Controllable via voice control available: Google Assistant or Amazon Alexa
- Controllable via LEDVANCE SMART+ WiFi Remote Controller
- High switching power: up to 2,990 W / 13 A
- Network protocol: WiFi
- Energy meter
- Scheduling




TECHNICAL DATA

Electrical data

| Nominal voltage | 230 V |
|-----------------|-------|
| Mains frequency | 50 Hz |

Dimensions & Weight



| Product weight | 95.00 g |
|----------------|---------|
| Length | 55 mm |
| Width | 55 mm |
| Height | 62 mm |

Lifespan

| Number of switching cycles | 100000 |
|----------------------------|--------|
| | |

Colors & materials

| Product color | White |
|---------------|---------|
| Body material | Plastic |

Temperatures & operating conditions

| Ambient temperature range | -10+35 °C |
|---------------------------|-----------|
|---------------------------|-----------|

Capabilities

| Compatible smart home technology | | Amazon Alexa / Google Assistant | |
|----------------------------------|--|---------------------------------|--|
| _ | | | |

Certificates & Standards

| Type of protection IP20 | Protec | ction class | 1 |
|-------------------------|--------|---------------|------|
| | Type | of protection | IP20 |

EQUIPMENT / ACCESSORIES

- For control via LEDVANCE SMART+ App, a smartphone or tablet is required (with minimum Android 8.0 or iOS 14.0)

Safety advice

- Disconnect devices which generate heat from the mains, i.e. from the SMART+ Plug, after use in order to avoid them being accidentally switched on
- Very high capacitive and inductive loads may in some cases lead to destruction of the device or reduction in the number of switching cycles.
- Do not use the SMART+ Plug in conjunction with medical equipment.
- To be connected to an automatic circuit breaker (max. 13 A).

DOWNLOAD DATA

| | Documents and certificates | Document name | |
|-----|-----------------------------|--------------------------------|--|
| POF | Extended installation guide | SMART+ WIFI INSTALLATION GUIDE | |
| POF | Declarations of conformity | EU Declaration of Conformity | |
| PDF | EU Data Act | SMART WiFi Plugs | |

LOGISTICAL DATA

| Product code | Packaging unit (Pieces/Unit) | Dimensions (length x width x height) | Gross weight | Volume |
|---------------|------------------------------|--------------------------------------|--------------|----------------------|
| 4058075566996 | Folding box | 61 mm x 78 mm x 96 mm | 140.00 g | 0.46 dm ³ |
| 4058075567009 | Shipping box 4 | 173 mm x 108 mm x 141 mm | 634.00 g | 2.63 dm ³ |

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

References / Links

- Further information and frequently asked questions (FAQs) at www.ledvance.com/consumer/smart/faq

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.